


Actuator and sensor cable, PUR-Connection cable, M12, A-coding, 4-pin



 Typecode
 M12A04CWF1ZU050N00

 ID
 1006050000112

Technical Data*

Connector A

Connector	Female, M12 x 1, angle, A-coding
Number of pins	4-pin
Contacts	Brass, Gold-plated
Coupling nut/screw	Zinc, Nickel-plated
Contact carriers	PA
Seal	No
Connector body	PUR, black
LED	No
Mechanical lifespan	≥100 Mating cycles
Pollution degree	3
Protection class	IP67, Only in screwed condition
Locking mode	Screw, M12 x 1
Standard	IEC 61076-2


Cable

Cable length	5.0 m
Cable diameter	Ø 5.00 mm ±0.20 mm
Cable jacket	PUR, black
Sheath stripping length	50 mm
Shielding	No
Core insulation	РР
Label for cables	L=20 mm, PVC
Core colors	1-BN, 2-WH, 3-BU, 4-BK
Conductor structure	43/0.10 mm, Bare copper, stranded
Core cross-section	4 x 0.34 mm ²

Features

- M12, Female, angle, 4-pin
 Stripping of cable tail jacket
 Cable jacket material: PUR
 Jacket color: black
 Resistant to chemicals and oils
 Resistant to salt spray
 Resistance to welding sparks
 Resistant to abrasion
 Suitable for mobile cabling applications
 Anti vibration
 Protection class: IP67
 ROHS-compliant
- Approval: cULus, CE

Cable structure





Technical Data

Electrical	properties

Electrical properties	
Connector rated voltage	250 V
Connector rated current	4 A
Connector insulation resistance	≥100 MΩ
Cable rated voltage	300 V
Cable test voltage	2000 V
Cable conductor resistance	≤55.4 Ω/km

Mechanical and chemical properties

Bending radius (stationary installation)	≥5xØ
Bending radius (fiexible use)	\geq 10 x Ø
Bending cycles	≥1 Mio.

Operation temperature

Ambient temperature range (stationary)	-40 °C 80 °C
Ambient temperature range (in motion)	-25 ℃ … 80 ℃


Commercial data

Country of origin	CN
Packaging unit	1 pc

Contact assignment



Connection diagram



* Please note that the data specified here were design data, and the parameters of product are subject to changes without prior notice. Matters not mentioned herein. Please contact customer service. Please also note that the user is responsible for validating functionality, conformity with applicable laws and directives, as well as for the electrical safety in the particular application.